

T4 Compact (continued) 

**EcoSystem® (5% dimming) universal voltage digital dimming ballasts**

- Dimming to 5%
- Compatible with Lutron 3-wire fluorescent controls and EcoSystem digital controls
- Energy saving

Lamp Watts	Lamps per Ballast	Model Number	Case Type*	Input Voltage (VAC)	Input Current (A)	Input Power (W)	Ballast Factor (BF)**	System Lumens (lm)†	System Efficacy (lm/W)†	Ballast Efficacy Factor (BEF)	Relative System Efficacy (RSE)
18 W (Triple/ Quad Tube)	1	<b>EC3D T418 K U 1 S‡</b>	K	277	0.08	20.8	0.95	1,140	55	4.57	0.82
				240	0.09	21.4	0.95	1,140	53	4.44	0.80
				120	0.18	21.3	0.95	1,140	54	4.46	0.80
	2	<b>EC3D T418 K U 2 S‡</b>	K	277	0.15	39.9	0.95	2,280	57	2.38	0.86
				240	0.17	39.4	0.95	2,280	58	2.41	0.87
				120	0.34	41.1	0.95	2,280	56	2.31	0.83
26 W (Triple/ Quad Tube)	1	<b>EC3D T4MW K U 1 S‡</b>	K	277	0.10	27.0	0.95	1,710	63	3.52	0.92
				240	0.11	26.9	0.95	1,710	64	3.54	0.92
				120	0.22	26.4	0.95	1,710	65	3.60	0.94
	2	<b>EC3D T4MW K U 2 S‡</b>	K	277	0.19	51.4	0.95	3,420	67	1.85	0.96
				240	0.21	50.6	0.95	3,420	68	1.88	0.98
				120	0.43	51.6	0.95	3,420	66	1.84	0.96
32 W (Triple Tube)	1	<b>EC3D T4MW K U 1 S‡</b>	K	277	0.12	33.2	0.95	2,280	69	2.86	0.91
				240	0.14	33.6	0.95	2,280	68	2.83	0.90
				120	0.29	34.8	0.95	2,280	66	2.73	0.87
	2	<b>EC3D T4MW K U 2 S‡</b>	K	277	0.24	65.5	0.95	4,560	70	1.45	0.93
				240	0.26	63.0	0.95	4,560	72	1.51	0.96
				120	0.55	66.0	0.95	4,560	69	1.44	0.92
42 W (Triple Tube)	1	<b>EC3D T442 K U 1 S‡</b>	K	277	0.15	42.6	0.95	3,040	71	2.23	0.94
				240	0.18	42.7	0.95	3,040	71	2.23	0.93
				120	0.36	43.2	0.95	3,040	70	2.20	0.92
	2	<b>EC3D T442 K U 2 S‡</b>	K	277	0.31	85.4	0.95	6,080	71	1.11	0.93
				240	0.35	85.1	0.95	6,080	72	1.12	0.94
				120	0.73	87.6	0.95	6,080	69	1.08	0.91

\*For case type information see pgs. 328-331.

\*\*Factory-tuned ballast factors available. To customize, visit [www.lutron.com/BallastTool](http://www.lutron.com/BallastTool)

†Actual number may vary with lamp model. Please consult the lamp manufacturer for lamp-specific data.

‡Mounting studs standard. Delete -S suffix in the model number if mounting studs are not needed.