

ELECTRONIC FLUORESCENT BALLASTS

For 13-18W T4 Quad Lamps

HIGH POWER FACTOR SOUND RATED A



No. of Lamps	Input Volts	Lamp Starting Method	Ballast Family	Catalog Number	Input Power ANSI (Watts)	Ballast Factor	Max. THD %	Line Current (Amps)	Min. Starting Temp. (°F/°C)	Dim.	Wiring Dia.
CFQ13W/G24q - 13W CFL Quad Tube Lamp (PL-C13W/4P, F13DBX/4P, CF13DD/E)											
1	120	RS	AmbiStar	RCF-2S13-M1-BS-QS	16	1.00	10	0.13	0/-18	Size I	160
	120-277		PS	SmartMate							
		ICF-2S13-H1-LD									
		ICF-2S13-H1-LD-K ⑩									
2	120	RS	AmbiStar	RCF-2S13-M1-BS-QS	29	1.00	10	0.25			
	120-277		PS	SmartMate					ICF-2S13-M1-BS-QS		
		ICF-2S13-H1-LD									
		ICF-2S13-H1-LD-K ⑩									
CFQ18W/G24q - 18W CFL Quad Tube Lamp (PL-C18W/4 P, F18DBX/4P, CF18DD/E)											
1	120	RS	AmbiStar	RCF-2S18-M1-BS-QS	19	1.00	10	0.16	0/-18	Size I	160
	120-277		PS	SmartMate							
		ICF-2S18-H1-LD									
		ICF-2S18-H1-LD-K ⑩									
2	120	RS	AmbiStar	RCF-2S18-M1-BS-QS	35	0.95	10	0.30			
	120-277		PS	SmartMate					ICF-2S18-M1-BS-QS		
		ICF-2S18-H1-LD									
		ICF-2S18-H1-LD-K ⑩									

⑩ Replacement/Retrofit ballast kits indicated with suffix K are available to distributors. Refer to page 3-20 for details.

Refer to page 3-26 for dimensions and wiring diagrams
 Refer to pages 9-23 to 9-27 for lead lengths and shipping data