

ELECTRONIC FLUORESCENT BALLASTS

For 26W Quad and 13W Triple T4 Lamps

HIGH POWER FACTOR SOUND RATED A



| No. of Lamps | Input Volts | Lamp Starting Method | Ballast Family | Catalog Number | Input Power ANSI (Watts) | Ballast Factor | Max. THD % | Line Current (Amps) | Min. Starting Temp. (°F/°C) | Dim. | Wiring Dia. |
|--|--------------------|----------------------|----------------|-------------------|--------------------------|----------------|------------|---------------------|-----------------------------|--------|-------------|
| CFQR26W/G24q - 26W CFL Quad Tube Lamp (PL-C26W/4P, F26DBX/4P, CF26DD/E) | | | | | | | | | | | |
| 1 | 120 | RS | AmbiStar | RCF-2S26-HI-LD-QS | 27 | 1.00 | 10 | 0.23 | 0/-18 | Size 1 | 160 |
| | | | | RCF-2S26-MI-BS-QS | | | | | | | |
| | 120-277 | PS | SmartMate | ICF-2S26-MI-BS-QS | 27 | 1.00 | 10 | 0.23-0.10 | | | |
| | | | | ICF-2S26-HI-LD | | | | | | | |
| | | | | ICF-2S26-HI-LD-K | | | | | | | |
| ICF-2S26-MI-BS | | | | | | | | | | | |
| 2 | 120 | RS | AmbiStar | RCF-2S26-HI-LD-QS | 51 | 1.00 | 10 | 0.43 | 0/-18 | Size 1 | 159 |
| | | | | RCF-2S26-MI-BS-QS | | | | | | | |
| | 120-277 | PS | SmartMate | ICF-2S26-MI-BS-QS | 51 | 1.00 | 10 | 0.43-0.19 | | | |
| | | | | ICF-2S26-HI-LD | | | | | | | |
| | | | | ICF-2S26-HI-LD-K | | | | | | | |
| | ICF-2S26-MI-BS | | | | | | | | | | |
| | ICF-2S42-M2-BS | 52 | 1.00 | 10 | 0.43-0.19 | Size 2 | | | | | |
| | ICF-2S42-M2-LD | | | | | | | | | | |
| | ICF-2S42-M2-LD-K | | | | | | | | | | |
| | ICF-2S42-90C-M2-BS | 52 | 1.00 | 10 | 0.43-0.19 | | | | | | |
| ICF-2S42-90C-M2-LD | | | | | | | | | | | |
| CFTR13W/GX24q - 13W CFL Triple Tube Lamp (FI3TBX/4P, CF13DT/E) | | | | | | | | | | | |
| 1 | 120 | RS | AmbiStar | RCF-2S13-MI-BS-QS | 16 | 1.00 | 10 | 0.13 | 0/-18 | Size 1 | 160 |
| | | | | ICF-2S13-MI-BS-QS | | | | | | | |
| | 120-277 | PS | SmartMate | ICF-2S13-HI-LD | 16 | 1.00 | 10 | 0.13-0.06 | | | |
| | | | | ICF-2S13-HI-LD-K | | | | | | | |
| ICF-2S13-MI-BS | | | | | | | | | | | |
| 2 | 120 | RS | AmbiStar | RCF-2S13-MI-BS-QS | 29 | 1.00 | 10 | 0.25 | 0/-18 | Size 1 | 159 |
| | | | | ICF-2S13-MI-BS-QS | | | | | | | |
| | 120-277 | PS | SmartMate | ICF-2S13-HI-LD | 29 | 1.00 | 10 | 0.25-0.11 | | | |
| | | | | ICF-2S13-HI-LD-K | | | | | | | |
| | | | | ICF-2S13-MI-BS | | | | | | | |

Replacement/Retrofit ballast kits indicated with suffix K are available to distributors. Refer to page 3-20 for details.

Refer to page 3-26 for dimensions and wiring diagrams
Refer to pages 9-23 to 9-27 for lead lengths and shipping data