

Application Ratings

UL/CSA Listed Application Ratings, Motor Protection Circuit Breaker Only

| Cat. No. | UL 508 — Manual Motor Controller | | | | | | | UL 508 Self-Protected (Type E) Combination Motor Controller | |
|----------------------|----------------------------------|---------------------------------|------|---------------------------------|------|---------------------------------|--------------------------|---|--------------------------|
| | Max. Fuse or C.B. per NEC | Group Motor Installation | | Motor Disconnect | | Tap Conductor Protection | | Max. Short Circuit Current [kA] | |
| | | Max. Short Circuit Current [kA] | | Max. Short Circuit Current [kA] | | Max. Short Circuit Current [kA] | | | |
| | | 480V | 600V | 480V | 600V | 480Y/277V ⁽¹⁾ | 600Y/347V ⁽¹⁾ | 480Y/277V ⁽¹⁾ | 600Y/347V ⁽¹⁾ |
| C-Frame | | | | | | | | | |
| 140M-C2E-A16 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-A25 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-A40 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-A63 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-B10 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-B16 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2E-B25 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-C2E-B40 | 450 | 65 | 25 | 65 | 25 | 65 | 25 | 65 | 25 |
| 140M-C2E-B63 | 450 | 65 | 30 | 65 | 30 | 65 | — | 65 | — |
| 140M-C2E-C10 | 450 | 65 | 30 | 65 | 30 | 65 | — | 65 | — |
| 140M-C2E-C16 | 450 | 30 | 30 | 30 | 30 | 30 | — | 30 | — |
| 140M-C2E-C20 | 450 | 30 | 30 | 10 | 10 | 10 | — | 10 | — |
| 140M-C2E-C25 | 450 | 25 | 10 | 10 | 5 | — | — | — | — |
| 140M-C2E-C29 | 450 | 25 | 5 | 10 | — | — | — | — | — |
| 140M-C2E-C32 | 450 | 25 | 5 | 10 | — | — | — | — | — |
| 140M-C2T-A16 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2T-A25 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2T-A40 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2T-A63 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2T-B10 | 450 | 65 | 47 | 65 | 47 | 65 | 47 | 65 | 47 |
| 140M-C2T-B16 | 450 | 65 | 47 | 65 | 47 | 65 | 30 | 65 | 30 |
| 140M-C2T-B25 | 450 | 65 | 25 | 65 | 25 | 65 | 25 | 65 | 25 |
| 140M-C2T-B40 | 450 | 65 | 30 | 65 | 30 | 65 | — | 65 | — |
| 140M-C2T-B63 | 450 | 65 | 30 | 65 | 30 | 65 | — | 65 | — |
| 140M-C2T-C10 | 450 | 30 | 30 | 30 | 30 | 30 | — | 30 | — |
| 140M-C2T-C16 | 450 | 30 | 30 | 10 | 10 | 10 | — | 10 | — |
| D-Frame (D8E) | | | | | | | | | |
| 140M-D8E-B25 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-D8E-B40 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-D8E-B63 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-D8E-C10 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-D8E-C16 | 450 | 65 | 30 | 65 | 30 | 65 | 30 | 65 | 30 |
| 140M-D8E-C20 | 450 | 65 | 30 | 65 | 30 | 65 | — | 65 | — |
| 140M-D8E-C25 | 450 | 30 | 30 | 30 | 30 | 30 | — | 30 | — |
| 140M-D8E-C29 | 450 | 30 | 30 | 30 | 18 | — | — | — | — |
| 140M-D8E-C32 | 450 | 30 | 30 | 30 | 18 | — | — | — | — |

(1) For full voltage (delta) ratings above 277V or 347V, follow the NEC or CEC rules for group motor applications.

UL Listed Application Ratings - Motor Protection Circuit Breakers with Bulletin 100-K Contactors

| Cat. No. | UL 508 — Manual Motor Controller | | | | | | UL508 Type F Combination Motor Controller | | |
|----------------|----------------------------------|------------------------|---------------------------------|------|---------------------------------|------|---|---------------------------------|--------------------------|
| | Max. Fuse or C.B. per NEC | Minimum Contactor Size | Group Motor Installation | | Motor Disconnect | | Minimum Contactor Size | Max. Short Circuit Current [kA] | |
| | | | Max. Short Circuit Current [kA] | | Max. Short Circuit Current [kA] | | | Max. Short Circuit Current [kA] | |
| | | | 480V | 600V | 480V | 600V | | 480Y/277V ⁽¹⁾ | 600Y/347V ⁽¹⁾ |
| C-Frame | | | | | | | | | |
| 140M-C2E-A16 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-A25 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-A40 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-A63 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-B10 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-B16 | 450 | 100-K05 | 65 | 47 | 65 | 47 | 100-K05 | 65 | 47 |
| 140M-C2E-B25 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | 30 |
| 140M-C2E-B40 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | 30 |
| 140M-C2E-B63 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | — |
| 140M-C2E-C10 | 450 | 100-K09 | 65 | 30 | 65 | 30 | 100-K09 | 65 | — |
| 140M-C2E-C16 | 450 | 100-K12 | 30 | 30 | 30 | 30 | 100-K12 | 30 | — |
| D-Frame | | | | | | | | | |
| 140M-D8E-B25 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | 30 |
| 140M-D8E-B40 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | 30 |
| 140M-D8E-B63 | 450 | 100-K05 | 65 | 30 | 65 | 30 | 100-K05 | 65 | 30 |
| 140M-D8E-C10 | 450 | 100-K09 | 65 | 30 | 65 | 30 | 100-K09 | 65 | 30 |
| 140M-D8E-C16 | 450 | 100-K12 | 65 | 30 | 65 | 30 | 100-K12 | 65 | 30 |

(1) For full voltage (delta) ratings above 277V or 347V, follow the NEC or CEC rules for group motor applications.

UL Listed Application Ratings - Motor Protection Circuit Breakers with Bulletin 100-C Contactors

| Cat. No. | UL 508 — Manual Motor Controller | | | | | | UL508 Type F Combination Motor Controller | | | | UL508 Type E Self-Protected Combination Motor Controller | | |
|----------------|----------------------------------|------------------------|---------------------------------|------|---------------------------------|------|---|---------------------------------|--------------------------|------------------------|--|--------------------------|--|
| | Max. Fuse or C.B. per NEC | Minimum Contactor Size | Group Motor Installation | | Motor Disconnect | | Minimum Contactor Size | Max. Short Circuit Current [kA] | | Minimum Contactor Size | Max. Short Circuit Current [kA] | | |
| | | | Max. Short Circuit Current [kA] | | Max. Short Circuit Current [kA] | | | Max. Short Circuit Current [kA] | | | Max. Short Circuit Current [kA] | | |
| | | | 480V | 600V | 480V | 600V | | 480Y/277V ⁽¹⁾ | 600Y/347V ⁽¹⁾ | | 480Y/277V ⁽¹⁾ | 600Y/347V ⁽¹⁾ | |
| C-Frame | | | | | | | | | | | | | |
| 140M-C2E-A16 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-A25 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-A40 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-A63 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-B10 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-B16 | 450 | 100-C09 | 65 | 47 | 65 | 47 | 100-C09 | 65 | 47 | 100-C09 | 65 | 47 | |
| 140M-C2E-B25 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | 100-C09 | 65 | 30 | |
| 140M-C2E-B40 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | — | 65 | 25 | |
| 140M-C2E-B63 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | — | — | 65 | — | |
| 140M-C2E-C10 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | — | — | 65 | — | |
| 140M-C2E-C16 | 450 | 100-C12 | 30 | 30 | 30 | 25 | 100-C12 | 30 | — | — | 30 | — | |
| 140M-C2E-C20 | 450 | 100-C16 | 30 | 30 | 30 | 30 | 100-C23 | 10 | — | — | 10 | — | |
| 140M-C2E-C25 | 450 | 100-C23 | 30 | 30 | 10 | 10 | — | — | — | — | — | — | |
| | 450 | 100-C30 | 30 | 30 | 30 | 30 | — | — | — | — | — | — | |
| 140M-C2E-C29 | 450 | 100-C30 | 10 | 5 | 10 | 5 | — | — | — | — | — | — | |
| 140M-C2E-C32 | 450 | 100-C37 | 10 | 5 | 10 | 5 | — | — | — | — | — | — | |
| D-Frame | | | | | | | | | | | | | |
| 140M-D8E-B25 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | 100-C09 | 65 | 30 | |
| | — | — | — | — | — | — | — | — | — | 100-C23 | 65 | 30 | |
| 140M-D8E-B40 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | 100-C23 | 65 | 30 | |
| 140M-D8E-B63 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-D8E-C10 | 450 | 100-C09 | 65 | 30 | 65 | 30 | 100-C09 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-D8E-C16 | 450 | 100-C12 | 65 | 30 | 65 | 30 | 100-C12 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-D8E-C20 | 450 | 100-C23 | 65 | 30 | 65 | 30 | 100-C23 | 65 | — | 100-C30 | 65 | — | |
| 140M-D8E-C25 | 450 | 100-C23 | 65 | 30 | 65 | 30 | 100-C23 | 30 | — | 100-C30 | 30 | — | |
| 140M-D8E-C29 | 450 | 100-C30 | 65 | 10 | 65 | 10 | — | — | — | — | — | — | |
| 140M-D8E-C32 | 450 | 100-C37 | 65 | 10 | 65 | 10 | — | — | — | — | — | — | |
| F-Frame | | | | | | | | | | | | | |
| 140M-F8E-C10 | 600 | 100-C30 | 65 | 30 | 65 | 30 | 100-C30 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-F8E-C16 | 600 | 100-C30 | 65 | 30 | 65 | 30 | 100-C30 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-F8E-C20 | 600 | 100-C30 | 65 | 30 | 65 | 30 | 100-C30 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-F8E-C25 | 600 | 100-C30 | 65 | 30 | 65 | 30 | 100-C30 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-F8E-C32 | 600 | 100-C30 | 65 | 30 | 65 | 30 | 100-C30 | 65 | 30 | 100-C30 | 65 | 30 | |
| 140M-F8E-C45 | 600 | 100-C37 | 65 | 18 | 65 | 18 | 100-C37 | 65 | — | 100-C37 | 65 | — | |

(1) For full voltage (delta) ratings above 277V or 347V, follow the NEC or CEC rules for group motor applications.

Definition of Type 2 Short Circuit Coordination:

- The contactor or starter must not endanger persons or plant in the event of a short circuit.
- No damage to the motor protection device or other parts may occur with the exception of welding of the contactor or starter contacts if these can be easily separated without appreciable deformation (such as with a screwdriver).

In the event of short circuit, fast-opening, current-limiting Bulletin 140M Motor Protection Circuit Breakers make it possible to build economical, fully short-circuit coordinated starter combinations with Type 2 coordination.

Type 2 Coordination, 400V

| Cat. No. | | | Max. Short-Circuit Current [kA] | Minimum Contactor Size |
|---------------------------|------------------------------|--------------------------|---------------------------------|------------------------|
| Standard Motor Protection | High Inrush Motor Protection | Motor Circuit Protection | 400V | |
| C-Frame | | | | |
| 140M-C2E-A16 | — | 140M-C2N-A16 | 100 | 100-C09 |
| 140M-C2E-A25 | 140M-C2T-A16 | 140M-C2N-A25 | 100 | 100-C09 |
| 140M-C2E-A40 | 140M-C2T-A25 | 140M-C2N-A40 | 100 | 100-C09 |
| 140M-C2E-A63 | 140M-C2T-A40 | 140M-C2N-A63 | 100 | 100-C09 |
| 140M-C2E-B10 | 140M-C2T-A63 | 140M-C2N-B10 | 100 | 100-C09 |
| 140M-C2E-B16 | 140M-C2T-B10 | 140M-C2N-B16 | 100 | 100-C09 |
| 140M-C2E-B25 | 140M-C2T-B16 | 140M-C2N-B25 | 50 | 100-C09 |
| 140M-C2E-B40 | 140M-C2T-B25 | — | 50 | 100-C09 |
| 140M-C2E-B63 | 140M-C2T-B40 | — | 50 | 100-C09 |
| 140M-C2E-C10 | 140M-C2T-B63 | — | 50 | 100-C09 |
| 140M-C2E-C16 | 140M-C2T-C10 | — | 50 | 100-C12 ⁽¹⁾ |
| 140M-C2E-C20 | 140M-C2T-C16 | — | 50 | 100-C23 |
| 140M-C2E-C25 | — | — | 15 | 100-C30 |
| 140M-C2E-C29 | — | — | 15 | 100-C30 |
| 140M-C2E-C32 | — | — | 15 | 100-C37 |
| D-Frame | | | | |
| 140M-D8E-B25 | — | 140M-D8N-B25 | 100 | 100-C09 |
| 140M-D8E-B40 | — | 140M-D8N-B40 | 100 | 100-C09 |
| 140M-D8E-B63 | — | 140M-D8N-B63 | 100 | 100-C09 |
| 140M-D8E-C10 | — | 140M-D8N-C10 | 65 | 100-C09 |
| 140M-D8E-C16 | — | 140M-D8N-C16 | 65 | 100-C12 |
| 140M-D8E-C20 | 140M-D8T-C16 | — | 65 | 100-C23 |
| 140M-D8E-C25 | 140M-D8T-C20 | 140M-D8N-C25 | 50 | 100-C23 |
| 140M-D8E-C29 | — | — | 65 | 100-C30 |
| 140M-D8E-C32 | — | 140M-D8N-C32 | 65 | 100-C37 |
| F-Frame | | | | |
| 140M-F8E-C10 | — | — | 100 | 100-C09 |
| 140M-F8E-C16 | — | — | 100 | 100-C12 |
| 140M-F8E-C20 | — | — | 100 | 100-C23 |
| 140M-F8E-C25 | — | 140M-F8N-C25 | 100 | 100-C30 |
| 140M-F8E-C32 | 140M-F8T-C25 | 140M-F8N-C32 | 100 | 100-C30 |
| 140M-F8E-C45 | 140M-F8T-C32 | 140M-F8N-C45 | 100 | 100-C37 |

(1) Cat. No. 100-C16 contactors Type 1 only

Type 2 Coordination, 480V

| Cat. No. | | | Max. Short-Circuit Current [kA] | Minimum Contactor Size |
|---------------------------|------------------------------|--------------------------|---------------------------------|------------------------|
| Standard Motor Protection | High Inrush Motor Protection | Motor Circuit Protection | 480V | |
| C-Frame | | | | |
| 140M-C2E-A16 | — | 140M-C2N-A16 | 65 | 100-C09 |
| 140M-C2E-A25 | 140M-C2T-A16 | 140M-C2N-A25 | 65 | 100-C09 |
| 140M-C2E-A40 | 140M-C2T-A25 | 140M-C2N-A40 | 65 | 100-C09 |
| 140M-C2E-A63 | 140M-C2T-A40 | 140M-C2N-A63 | 65 | 100-C09 |
| 140M-C2E-B10 | 140M-C2T-A63 | 140M-C2N-B10 | 65 | 100-C09 |
| 140M-C2E-B16 | 140M-C2T-B10 | 140M-C2N-B16 | 65 | 100-C09 |
| 140M-C2E-B25 | 140M-C2T-B16 | 140M-C2N-B25 | 50 | 100-C16 |
| 140M-C2E-B40 | 140M-C2T-B25 | — | 50 | 100-C30 |
| 140M-C2E-B63 | 140M-C2T-B40 | — | 50 | 100-C30 |
| 140M-C2E-C10 | 140M-C2T-B63 | — | 50 | 100-C30 |
| 140M-C2E-C16 | 140M-C2T-C10 | — | 10 | 100-C30 |
| 140M-C2E-C20 | 140M-C2T-C16 | — | 10 | 100-C30 |
| 140M-C2E-C25 | — | — | 10 | 100-C30 |
| 140M-C2E-C29 | — | — | 10 | 100-C30 |
| 140M-C2E-C32 | — | — | 10 | 100-C37 |
| D-Frame | | | | |
| 140M-D8E-B25 | — | 140M-D8N-B25 | 65 | 100-C09 |
| 140M-D8E-B40 | — | 140M-D8N-B40 | 65 | 100-C09 |
| 140M-D8E-B63 | — | 140M-D8N-B63 | 65 | 100-C09 |
| 140M-D8E-C10 | — | 140M-D8N-C10 | 65 | 100-C09 |
| 140M-D8E-C16 | — | 140M-D8N-C16 | 65 | 100-C12 |
| 140M-D8E-C20 | 140M-D8T-C16 | — | 65 | 100-C23 |
| 140M-D8E-C25 | 140M-D8T-C20 | 140M-D8N-C25 | 65 | 100-C23 |
| 140M-D8E-C29 | — | — | 65 | 100-C30 |
| 140M-D8E-C32 | — | 140M-D8N-C32 | 65 | 100-C37 |
| F-Frame | | | | |
| 140M-F8E-C10 | — | — | 65 | 100-C09 |
| 140M-F8E-C16 | — | — | 65 | 100-C12 |
| 140M-F8E-C20 | — | — | 65 | 100-C23 |
| 140M-F8E-C25 | — | 140M-F8N-C25 | 65 | 100-C30 |
| 140M-F8E-C32 | 140M-F8T-C25 | 140M-F8N-C32 | 65 | 100-C30 |
| 140M-F8E-C45 | 140M-F8T-C32 | 140M-F8N-C45 | 65 | 100-C37 |

Type 2 Coordination, 600V

| Standard Motor Protection | Cat. No. | | Max. Short-Circuit Current [kA] | Minimum Contactor Size |
|---------------------------|---------------------------------|--------------------------|------------------------------------|------------------------|
| | High Inrush Motor Protection | Motor Circuit Protection | 600V | |
| C-Frame | | | | |
| 140M-C2E-A16 | — | 140M-C2N-A16 | 47 | 100-C09 |
| 140M-C2E-A25 | 140M-C2T-A16 | 140M-C2N-A25 | 47 | 100-C09 |
| 140M-C2E-A40 | 140M-C2T-A25 | 140M-C2N-A40 | 47 | 100-C09 |
| 140M-C2E-A63 | 140M-C2T-A40 | 140M-C2N-A63 | 47 | 100-C09 |
| 140M-C2E-B10 | 140M-C2T-A63 | 140M-C2N-B10 | 47 | 100-C09 |
| 140M-C2E-B16 | 140M-C2T-B10 | 140M-C2N-B16 | 47 | 100-C09 |
| 140M-C2E-B25 | 140M-C2T-B16 | 140M-C2N-B25 | 10 | 100-C16 |
| 140M-C2E-B40 | 140M-C2T-B25 | — | 10 | 100-C16 |
| 140M-C2E-B63 | 140M-C2T-B40 | — | 5 | 100-C23 |
| 140M-C2E-C10 | 140M-C2T-B63 | — | 5 | 100-C30 |
| 140M-C2E-C16 | 140M-C2T-C10 | — | 5 | 100-C30 |
| 140M-C2E-C20 | 140M-C2T-C16 | — | 5 | 100-C30 |
| 140M-C2E-C25 | — | — | 5 | 100-C30 |
| 140M-C2E-C29 | — | — | 5 | 100-C30 |
| 140M-C2E-C32 | — | — | 5 | 100-C37 |
| D-Frame | | | | |
| 140M-D8E-B25 | — | 140M-D8N-B25 | 30 | 100-C30 |
| 140M-D8E-B40 | — | 140M-D8N-B40 | 30 | 100-C30 |
| 140M-D8E-B63 | — | 140M-D8N-B63 | 30 | 100-C30 |
| 140M-D8E-C10 | — | 140M-D8N-C10 | 30 | 100-C30 |
| 140M-D8E-C16 | — | 140M-D8N-C16 | 30 | 100-C30 |
| 140M-D8E-C20 | 140M-D8T-C16 | — | 5 | 100-C30 |
| 140M-D8E-C25 | 140M-D8T-C20 | 140M-D8N-C25 | 5 | 100-C30 |
| 140M-D8E-C29 | — | — | 10 | 100-C30 |
| 140M-D8E-C32 | — | 140M-D8N-C32 | 10 | 100-C37 |
| F-Frame | | | | |
| 140M-F8E-C10 | — | — | 30 | 100-C30 |
| 140M-F8E-C16 | — | — | 30 | 100-C30 |
| 140M-F8E-C20 | — | — | 30 | 100-C30 |
| 140M-F8E-C25 | — | 140M-F8N-C25 | 30 | 100-C30 |
| 140M-F8E-C32 | 140M-F8T-C25 | 140M-F8N-C32 | 30 | 100-C30 |
| 140M-F8E-C45 | 140M-F8T-C32 | 140M-F8N-C45 | 10 | 100-C37 |