

Open Type and Non-Combination Enclosed (IP65, Type 4/12) Controllers — For use with Line-Connected Motors, Continued

Enclosures other than those listed are available; consult your local Rockwell Automation sales office or Allen-Bradley distributor.

Rated Voltage [V AC]	Motor Current [A]⊛	Max. kW, 50 Hz	Max. Hp, 60 Hz	Control Power	Open Type — Line-Connected Motors*	IP65 (Type 4/12) Enclosed Non-Combination Controllers§ ➤
					Cat. No.	Cat. No.
400/415/460	1...5	2.2	3	100...240V AC, 50/60 Hz	150-F5NBD	150-F5FBD
				24V AC/DC♣	150-F5NBR	—
	5...25	11	15	100...240V AC, 50/60 Hz	150-F25NBD	150-F25FBD
				24V AC/DC♣	150-F25NBR	—
	8.6...43	22	30	100...240V AC, 50/60 Hz	150-F43NBD	150-F43FBD
				24V AC/DC♣	150-F43NBR	—
	12...60	30	40	100...240V AC, 50/60 Hz	150-F60NBD	150-F60FBD
				24V AC/DC♣	150-F60NBR	—
	17...85	45	60	100...240V AC, 50/60 Hz	150-F85NBD	150-F85FBD
				24V AC/DC♣	150-F85NBR	—
	27...108	55	75	100...240V AC, 50/60 Hz	150-F108NBD	150-F108FBD
				24V AC/DC♣	150-F108NBR	—
	34...135	75	100	100...240V AC, 50/60 Hz	150-F135NBD	150-F135FBD
				24V AC/DC♣	150-F135NBR	—
	67...201	110	150	100...240V AC, 50/60 Hz	150-F201NBD	150-F201FBD
				24V AC/DC♣	150-F201NBR	—
	84...251	132	200	100...240V AC, 50/60 Hz	150-F251NBD	150-F251FBD
				24V AC/DC♣	150-F251NBR	—
	106...317	160	250	100...240V AC, 50/60 Hz	150-F317NBD	150-F317FBD
				24V AC/DC♣	150-F317NBR	—
120...361	200	300	100...240V AC, 50/60 Hz	150-F361NBD	150-F361FBD	
			24V AC/DC♣	150-F361NBR	—	
160...480	250	400	100...240V AC, 50/60 Hz	150-F480NBD	150-F480FBD	
			24V AC/DC♣	150-F480NBR	—	
208...625	355	500	110/120V AC, 50/60 Hz	150-F625NBE ⊛	150-F625JBE	
			230/240V AC, 50/60 Hz	150-F625NBA ⊛	150-F625JBA	
260...780	450	600	110/120V AC, 50/60 Hz	150-F780NBE ⊛	150-F780JBE	
			230/240V AC, 50/60 Hz	150-F780NBA ⊛	150-F780JBA	
323...970	560	800	110/120V AC, 50/60 Hz	150-F970NBE	—	
			230/240V AC, 50/60 Hz	150-F970NBA	—	
416...1250	710	1000	110/120V AC, 50/60 Hz	150-F1250NBE	—	
			230/240V AC, 50/60 Hz	150-F1250NBA	—	

* Controllers rated 108 A and greater are not equipped with line and load terminal lugs. See page 4-126 for terminal lug kits.

⊛ Motor FLA rating should fall within specified current range for unit to operate properly. Special consideration should be given when using a motor with a potentially high starting current (greater than ten times motor FLA) with the SMC Flex in the "Full Voltage" starting mode. Contact Rockwell Automation technical support for further guidance.

§ These controllers require a separate 100...240V, 50/60 Hz single-phase control source. To add a control circuit transformer to the enclosure, add the appropriate option code to the catalog string.

♣ Separate 120V or 240V single-phase power supply is required for fan operation.

➤ Line and load termination are provided as standard.

⊛ Available in IP54 (Type 12) enclosure only.