






• Revised •
07/20/15

Field Modification Kits NEMA, Reduced Voltage and Lighting



Selection

1
2
3
4
5
6
7
8
9


Starter/Contactor Auxiliary Contact Kits

Description	Class	Size	Type	Catalog Number	List Price \$
	14, 17, 18, 22, 25, 26, 30, 32, 36, 37, 40, 43, 83, 84, 87, 88	00-4	1 NO	49AB10	
			1 NC	49AB01	
			1 NC Early Break	49AB01EB	
			1 NC Late Break	49AB01LB	
			1 NC Extra Late Break	49AB01XLB	
			1 NO Extra Late Make	49AB10XLM	
			1 NO & 1 NC	49AB11	
			2 NO	49AB20	
			4 NO	49AB40	
			3 NO & 1 NC	49AB31	
			2 NO & 2 NC	49AB22	
			2 NO	3RH1921-1EA20	
			1 NO & 1 NC	3RH1921-1DA11	
			2 NC	3RH1921-1EA02	
	14, 17, 18, 22, 25, 26, 36, 37, 40, 43, 87, 88	5, 6	1 NO & 1 NC (Inside L or R)	49CAL18-11	
			1 NO & 1 NC (Outside L or R)	49CAL18-11B	
	14, 17, 18, 22, 25, 26, 40, 43	7, 8	1 NO/NC	49LCAC1PA	
			2 NO/NC	49LCAC2PA	
	LC	30	Front Mounted 1 NO/NC	3RH2911-1HA11	
			Side Mounted 1 NO/NC	3RH2911-1DA11	
			Side Mounted 1 NO/NC	3RH1921-1EA11	
	LE	20	1 NO/NC SPDT	CLM4097291	
		30	2 NO/NC SPDT	CLM4097292	
		60-400	1 NO & 1 NC	CLMFCAK11	
			2 NC	CLMFCAK02	
			2 NO	CLMFCAK20	
			1 Coil Clearing NO & NC	CLMFCK11	
		300-400 Amps	1 NO & 1 NC	CLMHCAK11	
			2 NC	CLMHCAK02	
			2 NO	CLMHCAK20	
			1 Coil Clearing NO & NC	CLMHCK11	

Disconnect Auxiliary Switch Kits

Description	Class	Disconnect Amp or CB Rating	Type	Catalog Number	List Price \$
Non-fusible or Fusible Type 	17, 25, 32, 37, 83, 84, 87, 88, LED, LEF, CMN, CMF	30 - 200A	2 NO/2 NC DPDT (NEMA A600)	HA261234	
MCP 	18, 26, 32, 37, 83, 84, 87, 88, LEB, CMB	3A-125A	1 NO/1 NC 240V	A02ED62	
		250A	1 NO/1 NC 480V	A02FD64	
		400A-600A	(2) 1 NO/1 NC SPDT-480V	A02JLD64	

Control Power Transformer Kits^{①③}

Description	Recommended Transformer Size		VA Rating	Catalog Number	List Price \$	Transformer Table			
	Control Size	Transformer VA				Primary Volts	Secondary Volts	Code	
 Transformer 50/60HZ	00-2½	45 or 50 ^②	45 VA	KT*050 ^{②③} KT*050P ^③ KT*100 KT*150 KT*200 KT*300 KT*500		120	24	1	
	3-3½	75	50 VA			208	24	G	
	4	150	100 VA			208	120	H	
	5-6	150	150 VA			240/480	24	4	
	7-8	300	200 VA			240/480	120	8	
	Lighting Control		300 VA			277	24	5	
	CLM		500 VA			277	120	7	
	20A, 2 - 12P	150	Replace * with code from Transformer table. Kits used with NEMA 1 general purpose lift-off cover type require extra wide enclosure. Class 14 Sizes 0-2½ Class 30 (2S2W) Sizes 0-2½ Class 30 (2S1W) Sizes 0-1½			600	24	6	
	30A, 3P	100				600	120	9	
	30A, 6 - 12P	200							
	60A, 3P	100							
	60A, 4 - 6P	150							
	60A, 8 - 12P	250							
	100/200A, 3P	200							
	100/200A, 5P	250							
	300/400A, 3P	250							
	LC & LE								
	LC 30A, 2-12P	100							
LE 20, 30, 60A, 3 & 4P	45								
LE 30A, 6P	45								
LE 30A, 9-12P	100								
LE 60A, 6-12P	150								
LE 100, 200A, 3P	100								
LE 300, 400A, 3P	150								

① Installation of CPTs may require a larger enclosure.
② 45VA transformer kits will include secondary but not primary fusing. Sizes 50VA and higher include

2-pole primary fusing and 1-pole secondary fusing.

③ For 24VAC control a minimum of 100VA CPT is required.