

70 mm Control Tower Stack Lights

These devices are designed to communicate application status, alerting you to critical equipment and system needs on the plant floor. They can be pre-assembled to save time or ordered as separate light and sound modules for customized field assembly.

Light Modules



855T - B 10 DN 3
a b c d

| a Housing Color | |
|--------------------|-------------|
| Code | Description |
| B | Black |
| G | Gray |

| b Voltage | |
|--------------|--|
| Code | Description |
| 00 | 0...250V AC/DC (use only with module code XN) |
| 12 | 12V AC/DC |
| 24 | 24V AC/DC |
| 10 | 120V AC |
| 20 | 240V AC |

| c Light Module Type | |
|------------------------|--|
| Code | Description |
| XN | Steady no lamp ⁽¹⁾ |
| DN | Steady incandescent |
| FN | Flashing incandescent |
| TL | Steady LED |
| GL | Flashing LED |
| RL | Rotating LED, simulated with fixed LEDs ⁽²⁾ |
| BR | Strobe |

| d Lens Color | |
|-----------------|-------------|
| Code | Description |
| 3 | Green |
| 4 | Red |
| 5 | Amber |
| 6 | Blue |
| 7 | Clear |
| 8 | Yellow |

(1) For Light Module Type Code XN, only Voltage Code 00 can be selected. Accepts LED module or incandescent lamp.

(2) For Light Module Type RL, only Voltage Codes 10 or 24 can be selected and Lens Color Codes 3, 4, or 5 can be selected.

Combined Light Modules with Piezo Sounder

All single-circuit modules contain a selected light option with a sound device that operates simultaneously. All two-circuit modules contain two circuits that allow for separate operation of light or sound. The piezo-style sound modules can be switched to pulsing or continuous sound with a DIP switch. The volume can be adjusted to either low (92 dbA) or high (107 dbA), via a DIP switch. UL Type 4/4X/13, IP65.



855T - B 10 DC 5
a b c d

| a Housing Color | |
|--------------------|-------------|
| Code | Description |
| B | Black |
| G | Gray |

| b Voltage | |
|--------------|-------------|
| Code | Description |
| 12 | 12V AC/DC |
| 24 | 24V AC/DC |
| 10 | 120V AC |
| 20 | 240V AC |

| c Combined Module Type ⁽¹⁾ | |
|--|--|
| Code | Description |
| DC | Steady incandescent with sound |
| DD | Two-circuit steady incandescent with sound |
| FC | Flashing incandescent with sound |
| TC | Steady LED with sound |
| GC | Flashing LED with sound |
| BC | Strobe with sound |

| d Lens Color | |
|-----------------|-------------|
| Code | Description |
| 3 | Green |
| 4 | Red |
| 5 | Amber |
| 6 | Blue |
| 7 | Clear |
| 8 | Yellow |

(1) The single-circuit combined light/with sound module uses one circuit in a stack. It can be used with a maximum of four light modules and must be placed in the top position of a stack. The two-circuit combined light/with sound module uses two circuits in a stack. It can be used with a maximum of three light modules and must be placed in the top position of a stack.